

- 1 ELECTRICAL CONTRACTOR SHALL INSTALL OCCUPANCY MOTION SENSOR SWITCH FOR CONTROL OF LIGHTS AS SHOWN, AND SHALL SET SWITCH FOR 15 MINUTES.
  - 2 ELECTRICAL CONTRACTOR SHALL INSTALL CEILING MOUNTED MOTION SENSOR SWITCH FOR CONTROL OF LIGHTS AS SHOWN, AND SHALL SET SWITCH FOR 30 MINUTES.
  - 3 CEILING MOUNTED IN-LINE FAN, REFER TO MECHANICAL DRAWINGS AND COORDINATE EXACT LOCATION. EXHAUST FAN SHALL BE CONTROLLED BY SAME DEVICE THAT CONTROLS LIGHTS IN RESTROOM.
  - 4 FURNISH AND INSTALL JUNCTION BOX, TOGGLE DISCONNECT SWITCH IN NON-VISIBLE LOCATION, AND FINAL CONNECTION FOR 120 VOLT SIGN. SIGN IS FURNISHED WITH INTERNAL GROUND FAULT PROTECTION BY SIGN MANUFACTURER PER N.E.C. ARTICLE 600.25(B). VERIFY EXACT LOCATION OF JUNCTION BOX WITH SIGN DETAILS ON ARCHITECTURAL DRAWINGS. (REUSE EXISTING JUNCTION BOX AND CONDUIT INTO SPACE IF ALREADY INSTALLED. VERIFY IN FIELD EXACT LOCATION ON CANOPY).
- NOTE:  
THE CIRCUIT FOR SIGNAGE MUST BE A DEDICATED 3-LINE CIRCUIT CONSISTING OF HOT, NEUTRAL, AND GROUND WIRES LEADING DIRECTLY TO THE PANEL.
- 5 CIRCUIT NON-SALES EXIT AND EMERGENCY/NIGHT LIGHT BATTERY BACKUP BALLAST TO LOCAL CIRCUIT AHEAD OF ALL SWITCHING.
  - 6 CIRCUIT FITTING ROOM AREA EXIT AND EMERGENCY/NIGHT LIGHT BATTERY BACKUP BALLAST TO CIRCUIT A-2.
  - 7 SPEAKERS IN DENIM AREA SHALL BE WALL MOUNTED WITH TOP OF SPEAKER 6" BELOW CEILING. VERIFY ALL REQUIREMENTS WITH ARCHITECT AND EQUIPMENT MANUFACTURER PRIOR TO WORK COMMENCEMENT.
  - 8 ELECTRICAL CONTRACTOR TO COORDINATE WITH MILLWORK/SIGN CONTRACTOR FOR EXACT REQUIREMENTS FOR ELECTRICAL CONNECTION OF DISPLAY SIGN LIGHTING. ELECTRICAL CONTRACTOR TO SUPPLY AND INSTALL ALL REQUIRED MATERIALS FOR ELECTRICAL CONNECTION. CIRCUIT AS SHOWN ON PLANS.
  - 9 CIRCUIT SALES NIGHT LIGHTS AND EXIT/EMERGENCY LIGHT BATTERY BACKUP BALLAST TO CIRCUIT A-4.
  - 10 CIRCUIT SALES NIGHT LIGHTS AND EXIT/EMERGENCY LIGHT BATTERY BACKUP BALLAST TO CIRCUIT A-6.
  - 11 CIRCUIT SALES NIGHT LIGHTS AND EXIT/EMERGENCY LIGHT BATTERY BACKUP BALLAST TO CIRCUIT A-8.
  - 12 CIRCUIT SALES NIGHT LIGHTS AND EXIT/EMERGENCY LIGHT BATTERY BACKUP BALLAST TO CIRCUIT A-10.
  - 13 EXIT SIGN SHALL BE TOP MOUNTED TO J-BOX SUSPENDED FROM CEILING, WITH BOTTOM OF FIXTURE 11'-2" A.F.F. AND 6" AWAY FROM FINISHED SOFFIT/PORTAL. COORDINATE WITH ARCHITECTURAL SHEETS.
  - 14 EXIT SIGN TO BE SURFACE MOUNTED ON CEILING 6" AWAY FROM FINISHED SOFFIT. LOCATION TO BE COORDINATED WITH ARCHITECTURAL ELEMENTS OF CEILING.

LIGHTING PLAN CODED NOTES

D

EXPRESS  
EXPRESS FASHION OPERATIONS, LLC  
d/b/a STORE DESIGN & CONSTRUCTION  
1 Express Drive Columbus, Ohio 43230  
Telephone: 614.474.4001  
Express.com

712  
PKG B  
FALL 2014  
130832


PROJECT INFORMATION:  
EXPRESS  
SPRINGFIELD TOWN CENTER  
6847 SPRINGFIELD MALL  
SPACE NO. 1-22049  
SPRINGFIELD, VA 22150  
NEW PACKAGE:  
DG GENERATION:  
94869 A/E PROJECT #:

REVISIONS:  
REQUIRED BY: BUILDING DEPARTMENT  
LANDLORD COMMENTS  
DATE: 05/13/14  
04/08/14  
05/06/14  
INDICATES NO REVISION TO THIS SHEET

M-Engineering  
750 Brookside Blvd.  
Westerville, Ohio 43081  
phone: 614.839.4639  
fax: 614.839.2222  
ELITE CONSTRUCTION GROUP  
LAKE JACKSON, TX  
PHONE: 979-385-0712  
NOTE: THESE PRINTS HAVE BEEN  
REDUCED BY 50 PERCENT SCALE  
WILL BE 50 PERCENT OF WHAT IS  
NOTED ON PLANS

DATE ISSUED: 02/14/2014  
DESIGNED BY: CDH  
DRAWN BY: CDH  
CHECKED BY: DFG

ELECTRICAL  
LIGHTING  
PLAN  
DRAWING NUMBER:  
E03.1



VERIFY ALL FIELD CONDITIONS PRIOR TO BID

1/4"=1'-0"

A