

NOTE:
REFER TO SHEET E04.01 FOR ELECTRICAL LIGHTING SCHEDULE AND LIGHT DESCRIPTIONS.

NOTE:
REFER TO SHEET E05.01 FOR PANEL SCHEDULE AND LIGHTING ZONE DESIGNATIONS.

NOTE:
ELECTRICAL CONTRACTOR SHALL REFER TO ARCHITECTURAL SHEETS FOR MOUNTING HEIGHTS AND INSTALLATION DETAILS FOR SUSPENDED LIGHTING IN NON-SALES AREA.

NOTE:
GENERAL CONTRACTOR SHALL VERIFY CEILING FIRE RATING WITH ARCHITECT, AND BOX OR TENT ALL RECESSED LIGHT FIXTURES, IF REQUIRED, TO MAINTAIN CEILING FIRE RATING.

LANDLOCK COMMENTS:
BACKLIT PATTERN TO BE ISOLATED/ AJUSTABLE "DIMMER"

- ① ELECTRICAL CONTRACTOR SHALL SET SWITCH FOR 15 MINUTES. MOUNT AT "44" AFF.
- ② CIRCUIT SALES EXIT AND EMERGENCY/NIGHT LIGHT BATTERY BACK-UP BALLAST TO CIRCUIT A-1
- ③ REFER TO SHEET E02.01 FOR VIEW-MONITOR-POWER REQUIREMENT. REFER TO ARCHITECTURAL RCP PLAN FOR EXACT LOCATION.
- ④ ELECTRICAL CONTRACTOR SHALL FURNISH AND INSTALL OUTLET FOR INTERNALLY ILLUMINATED LED GINGHAM TRANSOM STOREFRONT, CONNECTION TO TRANSFORMER. REFER TO ARCHITECTURAL DRAWINGS FOR MORE INFORMATION. MOUNTING HEIGHT FOR THE LED OUTLETS AT THE GINGHAM PANELS: TOP OF WALL, 3" BELOW CEILING.
- ⑤ CONTRACTOR TO ROTATE FIXTURES SO THAT UL LABELS ARE NOT VISIBLE TO CUSTOMER.
- ⑥ ELECTRICAL CONTRACTOR SHALL FURNISH AND INSTALL OUTLET FOR INTERNALLY ILLUMINATED LED GINGHAM ABOVE CANOPY & ON SIDE PANELS, CONNECTION TO TRANSFORMER. REFER TO ARCHITECTURAL DRAWINGS FOR MORE INFORMATION. MOUNTING HEIGHT FOR THE LED OUTLETS AT THE GINGHAM PANELS: TOP OF WALL, 3" BELOW CEILING.
- ⑦ PROVIDE 1000 WATT DIMMER FOR PENDANTS TO CONTROL PENDANT LIGHTS "FP".
- ⑧ FURNISH AND INSTALL JUNCTION BOX, TOGGLE DISCONNECT SWITCH IN NON-VISIBLE LOCATION, AND FINAL CONNECTION FOR 120 VOLT SIGN. SIGN IS FURNISHED WITH INTERNAL GROUND FAULT PROTECTION BY SIGN MANUFACTURER PER N.E.C. ARTICLE 600-236. VERIFY EXACT LOC ON BOX WITH SIGN MANUFACTURER, (REUSE EXISTING JUNCTION BOX AND CONDUIT INTO SPACE IF ALREADY INSTALLED. VERIFY IN FIELD EXACT LOCATION ON CANOPY). FOR CANOPY POWER SEE SHEET A08.01 FOR WALL PENETRATION IN ROUTING CONDUIT.
- NOTE:**
THE CIRCUIT FOR SIGNAGE MUST BE A DEDICATED ISOLATED 3-LINE CIRCUIT CONSISTING OF HOT, NEUTRAL, AND GROUND WIRES LEADING DIRECTLY TO THE PANEL.
- ⑨ LIGHT FIXTURES TO BE INSTALLED IN MILLWORK FIXTURE, NOT IN CEILING. VERIFY WITH LSO&C. REFER TO SHEET E02.01 FOR POWER REQUIREMENTS.
- ⑩ "AA" LIGHTS ARE REMODEL HOUSING AND DO NOT INSTALL DURING ROUGH FRAMING.
- ⑪ PROVIDE OCCUPANCY SENSOR TO AUTOMATICALLY TURN OFF WITHIN 30 MINUTES OF ALL OCCUPANTS LEAVING THE SPACE.
- ⑫ CIRCUIT NONSALES EXIT AND EMERGENCY/NIGHT LIGHT BATTERY BACKUP BALLAST TO LOCAL CIRCUIT AHEAD OF ALL SWITCHING.
- ⑬ CIRCUIT SALES EXIT AND EMERGENCY/NIGHT LIGHT BATTERY BACK-UP BALLAST TO CIRCUIT A-42

NTS
42N-E0301-D00-NOTE

D

ELITE CONSTRUCTION GROUP
LAKE JACKSON, TX
PHONE: 979-285-0712
NOTE: THESE PRINTS HAVE BEEN
REDUCED BY 50 PERCENT. SCALE
WILL BE 50 PERCENT OF WHAT IS
NOTED ON PLANS

Limitedbrands
LIMITED STORE PLANNING, INC.
d/b/a STORE DESIGN & CONSTRUCTION
 Three Limited Parkway • Columbus, Ohio 43230
 Telephone: 614.415.7000 • Fax: 614.415.7349



1/4" = 1'-0"

REVISIONS:		
	REQUIRED BY:	DATE
1	BUILDING DEPARTMENT COMMENTS	04/11/11
2	BUILDING DEPARTMENT COMMENTS	05/8/11
3	DESIGN CHANGES/ LANDLORD COMMENTS/ MASTERS UPDATES	05/28/11
4	DESIGN CHANGES	06/27/11
5	DESIGN CHANGES	07/24/11

ELECTRICAL LIGHTING PLAN

DRAWING NUMBER:
E03.01